## **CLAMP-ON METERS** 400 & 600 SERIES BLUETOOTH EDITION **POWER AND HARMONIC METERS**

#### MODELS 407 & 607

Now available with Android<sup>™</sup> mobile application

#### SPECIFICATIONS

MODELS	407 TRMS	607 TRMS
ELECTRICAL		
Current AC (rms)	1000A	2000A
Current DC	1500A	3000A
Current AC+DC	1500A Peak	3000A Peak
Voltage AC (rms)	1000V	1000V
Voltage DC	1000V	1000V
Voltage AC+DC	1000V	1000V
Ohms	100kΩ	100kΩ
Continuity (Buzzer)	Yes (< 40Ω)	Yes (< 40Ω)
Total Harmonic Distortion	Yes	Yes
Individual Harmonics (to 25th)	Yes	Yes
Single- and 3-Phase Real Power (AC, DC, AC/DC)*	1000kW	1000kW
Single- and 3-Phase Reactive Power (AC, DC, AC/DC)*	1000kvar	2000kvar
Single- and 3-Phase Apparent Power (AC, DC, AC/DC)*	1000kVA	2000kVA
Voltage Frequency (Hz)	20kHz	20kHz
Current Frequency (Hz)	2kHz	1kHz
Power Function (W, var, VA)	Yes	Yes
Power Factor	Yes	Yes
THD-r/THD-f	Yes	Yes
Auto AC/DC	Yes (V & A)	Yes (V & A)
Auto Power OFF	Yes	Yes
Hold Button	Yes	Yes
Backlight Button	Yes	Yes
Min/Max Button	Yes	Yes
True InRush <sup>®</sup> Function	Yes	Yes
Peak ± Function	Yes	Yes
Harmonics Function	Yes	Yes
Rec (Record) Function	Yes	Yes
Wireless BT (Bluetooth) Function	Yes	Yes
Record (Recordings)	1000	1000
Hz Button	Yes	Yes

\*3-phase measurements assume balanced load

### PRODUCT INCLUDES

#### MODELS 407 & 607

Hard carrying case, set of two color-coded silicone test leads, test probes and alligator clips, Bluetooth USB adapter, four 1.5V AA batteries, safety information sheet, and USB drive supplied with DataView® software and user manual.

Backlight E
Min/Max B
True InRus
Peak ± Fur
Harmonics
Rec (Recor
Wireless B
Record (Re

True InRus

400 & 600 Series Housing Only

 Measures harmonics up to the 25th Records up to 1000 measurements .

Measures frequency to 20kHz with

Auto selects AC or DC measurement

True InRush<sup>®</sup> current measurement with

Bluetooth communication -(communicates up to 30ft)

1000V CAT IV Rated

FEATURES

backlit display

(Model 607)

resolution to 1W

0.1Hz resolution

100mS capture

ь.

.

.

\*

 UL 94 VI flame retardant self-extinguishing 10,000-count blue electroluminescent

and AC+DC with resolution to 10mV Measures up to 2000Aac and 3000Aac

three-phase balanced systems

Measures up to 1000VAC (1400V peak), 1000VDC

Measures W, VA, var and PF for single- and

 Measures single- and three-phase power (real, reactive and apparent) up to 3MW with

- Includes FREE DataView<sup>®</sup> software for download and report generation
- Jaw opening up to 1.89" (48mm) (400 series) and up to 2.36" (60mm) (600 series)

#### CATALOG NO. DESCRIPTION

Power Clamp-On Meter Model 407 (TRMS, 1000Vac/dc, 1000Aac/1500Adc, Ohms, Continuity, Energy, Harmonics, Power, THD, Recording) Power Clamp-On Meter Model 607

(TRMS, 1000Vac/bc, 2000Aac/3000Abc, Ohms, Continuity, Energy, Harmonics, Power, THD, Recording)



2139.51

2139.61



# information@itm.com