

Bench Type Digital Multimeter



72-1055.



72-1012.



72-1015.

Features

- Manual Function Select or Auto Ranging
- Diode Test & Continuity Buzzer
- Transistor Test
- Data Hold
- LCD Backlight
- Low Battery Indications
- Input Impedance for DC Voltage: All Other Ranges: Around 10MΩ
600mV Range: Around 3GΩ (Only 72-1015 Model)
- Voltage & Current : AC + DC Measurement (Only 72-1015 Model)

Electrical Specifications

Parameter	72-1055.	72-1012.	72-1015.
DC Voltage (V)	200mV / 2V / 20V / 200V / 1000V ±(0.5%+2 digits)	200mV / 2V / 20V / 200V / 1000V ±(0.1%+3 digits)	600mV / 6V / 60V / 600V / 1000V ±(0.3% +2 digits)
AC Voltage (V)	2V / 20V / 200V / 750V ±(0.8% +3 digits)	2V / 20V / 200V / 750V ±(0.5% +20 digits)	600mV / 6V / 60V / 600V / 1000V ±(0.6% +5 digits)
DC Current (A)	200µA / 2mA / 20mA / 200mA / 10A ±(0.8% +2 digits)	200µA / 2mA / 20mA / 200mA / 10A ±(0.5% +20 digits)	600µA / 6000µA / 60mA / 600mA / 10A ±(0.5% +3 digits)
AC Current (A)	2mA / 20mA / 200mA / 10A ±(1% +3 digits)	2mA / 20mA / 200mA / 10A ±(0.8% +40 digits)	600µA / 6000µA / 60mA / 600mA / 10A ±(1% +5 digits)
Resistance (Ω)	200Ω / 2kΩ / 20kΩ / 200kΩ / 2MΩ/ 20MΩ ±(0.8% +3 digits)	200Ω / 2kΩ / 20kΩ / 200kΩ / 2MΩ/ 200MΩ ±(0.5% +10 digits)	600Ω / 6kΩ / 60kΩ / 600kΩ / 6MΩ / 60MΩ ±(0.5% +2 digits)
Capacitance (F)	20nF / 2µF / 200µF ±(4% +3 digits)	20nF / 2µF / 200µF ±(4% +10 digits)	6nF / 60nF / 600nF / 6µF / 60µF / 600µF / 6mF ±(2% +5 digits)
Frequency (Hz)	2kHz / 200kHz ±(1.5% +5 digits)	2kHz / 200kHz ±(1.2% +10 digits)	6kHz / 60kHz / 600kHz / 6MHz / 60MHz ±(0.1% +3 digits)
Temperature (°C)	-40°C ~ +1000°C ±(1.2% +3 digits)	-40°C ~ +1000°C ±(1.2% +25 digits)	-40°C ~ +1000°C ±(1% +3 digits)
Temperature (°F)		-	-40°F ~ 1832°C ±(1.5% +5 digits)

Newark.com/exclusive-brands
Farnell.com/exclusive-brands
Element14.com/exclusive-brands



Bench Type Digital Multimeter



Parameter	72-1055.	72-1012.	72-1015.
Display Count	2000	20000	6000
Ranging	Manual Range		Auto Range
True RMS	-		Yes
Misuse Alarm	Yes		-
Bandwidth	-		100kHz
Auto Power Off	-		Yes
MAX / MIN	-		Yes
RS - 232	-		Yes
USB Interface	-		Yes
Input Protection	-		Yes
Standard Accessories	Battery, Test Lead, Alligator Clip, Point Contact Temperature Probe, Multi-Purpose Socket, AC 120V Power Cord, Power Adaptor, Instruction Manual		Test Lead, Alligator Clip, Point Contact Temperature Probe, Multi-Purpose Socket, AC 120V Power Cord, Software, RS-232 Interface Cable, USB Interface Cable, Instruction Manual

General Characteristics

Parameter	72-1055.	72-1012.	72-1015.
Safety Rating	CAT II 1000V		CAT I 1000V, CAT II 600V
Power	AC 220V/50Hz or 1.5V Batteries (R14) × 6		AC 220V/50Hz or 1.5V Batteries (R14) × 6
LCD Size	108mm × 34.5mm		128mm × 28mm
Colour	Orange and Grey		
Weight	1.65kg		2.4kg
Dimension (H × W × L)	300mm × 105mm × 240mm		310mm × 105mm × 240mm

Part Number Table

Description	Part Number
Digital Multimeter, Bench Type	72-1055.
Digital Multimeter, Bench Type	72-1012.
True RMS Digital Multimeter, Bench Type	72-1015.

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell Limited 2016.

Newark.com/exclusive-brands
 Farnell.com/exclusive-brands
 Element14.com/exclusive-brands

