

True RMS Bench Top Digital Multimeter **TENMA™**



Features:

- 20000 Counts Display
- Manual Function Select & Ranging
- Duty Cycle: 1% to 99%
- Diode & Continuity Buzzer
- Transistor & SCR Measurement
- Data Hold
- EBTN LCD Backlight
- USB Interface
- Input Impedance for DC Voltage: Around 10MΩ

Electrical Specifications:

Parameter	Range
DC Voltage (V)	200mV/2V/20V/200V/1000V $\pm(0.1\% +3 \text{ digits})$
AC Voltage (V)	2V/20V/200V/750V $\pm(0.5\% +20 \text{ digits})$
DC Current (A)	200μA/2mA/20mA/200mA/20A $\pm(0.5\% +20 \text{ digits})$
AC Current (A)	2mA/20mA/200mA/20A $\pm(0.8\% +40 \text{ digits})$
Resistance (Ω)	200Ω/2kΩ/20kΩ/200kΩ/2MΩ/20MΩ $\pm(0.5\% +10 \text{ digits})$
	200Ω/2kΩ/20kΩ/200kΩ/2MΩ/200MΩ $\pm(0.5\% +10 \text{ digits})$
Capacitance (F)	20nF/200nF/2μF/20μF/200μF/2mF/20mF/100mF $\pm(2.5\% +10 \text{ digits})$
Frequency (Hz)	10Hz to 10MHz $\pm(1\% +4 \text{ digits})$

True RMS Bench Top Digital Multimeter

General Characteristics:

Safety Rating	: CAT II 600V
Power	: 100V/120V/220V/240V \pm 10%, 47Hz to 63Hz
Colour	: White and Grey
Weight	: 2.4kg
Dimensions (W x D x H)	: 380mm x 320mm x 110mm

Accessories:

Test Lead, Power Cord, PC Software CD, USB Interface Cable and Instruction Manual

Part Number Table

Description	Part Number
True RMS Bench Top Digital Multimeter	72-13625

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell Limited 2016.

www.element14.com
www.farnell.com
www.newark.com
www.cpc.co.uk

