



CAM TRACKING VIEW

NOTES

- 1-SWITCH IS ASSEMBLED FOR ACTUATION IN BOTH DIRECTIONS BUT MAY BE ADJUSTED TO ACTUATE IN EITHER THE CLOCKWISE DIRECTION ONLY OR THE COUNTERCLOCKWISE DIRECTION ONLY
- 2- TO CONVERT SWITCH FOR ACTUATION IN EITHER THE CLOCKWISE OR COUNTERCLOCKWISE DIRECTION ONLY, REMOVE ACTUATOR HEAD AND ROTATE THE NOTCHED PLUNGER 90° TO THE RIGHT FOR CLOCKWISE ACTUATION OR 90° TO THE LEFT FOR COUNTER-CLOCKWISE ACTUATION
- 3 ROLLER LEVER MAY BE LOCKED IN ANY POSITION THRU 360°
- 4-LEVER FURNISHED UNASSEMBLED IN UNIT PACKING BOX

THIS DRAWING COVERS A PROPRIETARY ITEM AND IS THE PROPERTY OF MICRO SWITCH, A DIVISION OF MINNEAPOLIS-HONEYWELL REGULATOR CO. THIS DRAWING IS NOT TO BE COPIED OR USED WITHOUT THE APPROVAL OF MICRO SWITCH.

CHARACTERISTICS	ELECTRICAL DATA	SCALE 1/2 TO 1
OPERATING TORQUE ----- 4.5 IN-LB	CONTACT ARRANGEMENT (SEE CIRCUIT DIAGRAM)	DO NOT SCALE PRINT
FULL OVERTRAVEL TORQUE----- 6 IN-LB		UNLESS OTHERWISE NOTED
RELEASE TORQUE----- .75 IN-LB		DIMENSIONS ARE IN INCHES
PRETRAVEL----- 20° MAX	10A-120, 240, OR 480 VAC, 1/3 HP - 120 VAC	<b>TOLERANCES ARE:</b>
DIFFERENTIAL TRAVEL----- 12° MAX	3/4 HP - 240 VAC; 0.8A - 115 VDC; 0.4A - 230 VDC	ONE PLACE (.0) ±.030
OVERTRAVEL----- 30° MIN	.1A - 550 VDC	TWO PLACE (.00) ±.015
RELEASE TRAVEL----- 5° MIN	PILOT DUTY: 600 VAC MAX	THREE PLACE (.000) ±.005
SWITCH-BASIC REPLACEMENT ----- 2MNI		ANGLES ±
		WEIGHT

FORMTEK  
 FO-50378-003  
 DRAWN  
 LLD 12 JUN 64  
 CHECK  
 PAW 24 JUNE 64  
 CHECK  
 ISSUE 16  
 DRAWING NUMBER  
 M  
 7LS1  
 PAGE 1 OF 1  
 RELEASE NO.  
 REVISIONS  
 A CO-195463-B  
 D L  
 7 SEP 99  
 REPLACES