Email: Sales@linengineering.com | Techsupport@linengineering.com


www.linengineering.com



Motor Specifications

Part Number	BL23E33-01-R0
Dimension "A" Max	3.29 in [83.5mm]
Rated Voltage	24 VDC
Rated Torque	41.07 oz-in [0.29N-m]
Rated Speed	4000 RPM
Rated Power	120 Watts
Rated Current	6.9 Amps
Peak Torque	82.13 oz-in [0.58N-m]
Peak Current	13.8 Amps
Torque Constant (kt)	5.95 oz-in/Amp
Back EMF Constant (Ke)	4.23 Vp/KRPM
Motor Constant (Km)	14.02 oz-in/√W [0.099 N-m/√W]
Resistance	0.18 Ohms
Inductance	0.18 mH
Rotor Inertia	1.53 oz-in ²
Weight	2.38 lb [1.08 kg]
Electrical Time Constant	1 ms
Mechanical Time Constant	3 ms

Dimensions



Performance Curve

Recommended Products



BLDC100-BL23E33-01



Speed (RPM)

BLDC EXTENSION CABLE **4201-100/300**

Motor Operating Specs.

Hall Effect Angle	120°Ω electrical Angle
Radial Play	0.002 in [0.05 mm] @ 0.99 lbs [0.45 kg]
End Play	0.003 in [0.08 mm] @ 99.21 lbs [45.00 kg]
Max. Radial Force	0.787 in [20.00 mm] @ 16.80 lbs [7.62 kg]
Max. Axial Force	3.37 lbs [1.53 kg]
Insulation Class	Class B
Dielectric Strength	500 VDC for 1 minute
Insulation Resistance	100Ω min. $500VDC$
Ambient Operating Temperature	-20°C to 50°C
Storage Temperature	-20°C to 100°C
Humidity Range (%)	85% (RH) non-condensing
Direction of Rotation	CCW

Pin Out Charts

PIN#	COLOR	PHASE
1	RED	VCC (+5V)
2	YELLOW	HV
3	BLUE	HW
4	BLACK	GND
5	ORANGE	HU

PIN#	COLOR	PHASE
1	BLUE	W
2	ORANGE	U
5	YELLOW	V

Operation & Usage Tips



Do not disassemble motors; a significant reduction in motor performance will occur.



Do not machine shafts; this will have a negative effect on shaft run out and perpendicularity.



Do not disconnect motor from drive while in operation.



Do not use holding torque/detent torque of motor as a fail safe brake



Do not hold motor by lead wires.



Do not exceed the rated current; this wil burn the motor.

FAILURE TO COMPLY WITH THESE RECOMMENDATIONS WILL VOID ALL WARRANTY TERMS

Motion Control, Solved.

MOTOR ENGINEERING & MANUFACTURING







Small Batch to OEM Volume Production

