

# MEGOHMMETERS

500V & 1000V Hand-cranked

## Models 6501 & 6503

Designed for acceptance testing and preventive maintenance of wiring, cables, switchgear and motors

### SPECIFICATIONS

MODELS	6501	6503	
<b>INSULATION TESTS</b>			
Test Ranges*	250V 500V 1000V	– 0.5 to 200MΩ –	1 to 500MΩ 1 to 500MΩ 10 to 5000MΩ
Short Circuit Current	5mA (max)		
Voltage Measurement/ Safety Check	0 to 600Vac		
Accuracy (MΩ)	±2.5% of Full Scale Length		
Automatic Discharge	5s/μF	8s/μF	
Charge Time	250V 500V 1000V	– 0.5s/μF –	0.2s/μF 0.5s/μF 0.5s/μF
<b>RESISTANCE TESTS</b>			
Measurement Range	0 to 45kΩ; 45 to 500kΩ	–	
Test Current	1mA <sub>DC</sub>	–	
Accuracy	±2.5% of Full Scale Length	–	
<b>CONTINUITY TESTS</b>			
Measurement Range	0 to 9Ω; 10 to 100Ω	–	
Test Voltage	5mA <sub>DC</sub> (10V max)	–	
Accuracy	±2.5% of Full Scale Length	–	

\*DC test voltage generated 5.5 to 200MΩ in full across the entire measurement range.

### PRODUCT INCLUDES

Soft carrying case, test leads, blue lead (for use with Model 6503), alligator clips, test probe, and user manual.



### FEATURES

- True Megohmmeter®
- Test voltages of 250V, 500V and 1000V (model dependent)
- Insulation measurements to 200MΩ and 5000MΩ (model dependent)
- LED indicates constant voltage output and proper cranked speed controlled by voltage regulator
- Automatic discharge when measurement is finished
- Auto-Ranging – dual scale operation for better sensitivity and easier readings
- Compact self-contained package; folded crank
- Voltage displayed prior to, during and at the end of test
- Large direct reading scale
- EN 61010-1, 600V CAT II, 300V CAT III

CATALOG NO.	DESCRIPTION
2126.51	Megohmmeter Model 6501 (Hand-cranked, 500V, Resistance, Continuity)
2126.52	Megohmmeter Model 6503 (Hand-cranked, 250V, 500V, 1000V)

Test Equipment Depot - 800.517.8431  
99 Washington Street, Melrose, MA 02176  
[TestEquipmentDepot.com](http://TestEquipmentDepot.com)



AEMC MODEL NUMBER	AEMC CATALOG NUMBER	TEST VOLTAGE	INSULATION RANGE	RESISTANCE RANGE	CONTINUITY RANGE	CAPACITANCE RANGE	VOLTAGE DETECTION	POWER SOURCE	DISPLAY	DATAVIEW® SOFTWARE
1050	2130.01	50V 100V 250V 500V 1000V	2kΩ to 200GΩ 4kΩ to 400GΩ 10kΩ to 1TΩ 20kΩ to 2TΩ 40kΩ to 4TΩ	0.01 to 400kΩ	0.01 to 39.99Ω	0.005 to 4.999μF	0 to 1000VAc/dc	8 x 1.5V C Cell Batteries	Digital/ Analog	No
1060	2130.03	50V 100V 250V 500V 1000V	2kΩ to 200GΩ 4kΩ to 400GΩ 10kΩ to 1TΩ 20kΩ to 2TΩ 40kΩ to 4TΩ	0.01 to 400kΩ	0.01 to 39.99Ω	0.005 to 4.999μF	0 to 1000VAc/dc	Rechargeable NiMH Battery	Digital/ Analog	Yes
5050	2130.20	500V 1000V 2500V 5000V	30kΩ to 2TΩ 100kΩ to 4TΩ 100kΩ to 10TΩ 300kΩ to 10TΩ	—	—	0 to 49.99μF	2500VAc 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	No
5060	2130.21	500V 1000V 2500V 5000V	30kΩ to 2TΩ 100kΩ to 4TΩ 100kΩ to 10TΩ 300kΩ to 10TΩ	—	—	0 to 49.99μF	2500VAc 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	Yes
5070	2130.30	500V 1000V 2500V 5000V	30kΩ to 2TΩ 100kΩ to 4TΩ 100kΩ to 10TΩ 300kΩ to 10TΩ	—	—	0 to 49.99μF	2500VAc 4000Vdc	Rechargeable NiMH Battery	Graphic/ Digital	Yes
6501	2126.51	500V	0.5 to 200MΩ	0 to 500kΩ	0 to 100Ω	—	0 to 600VAc	Hand-cranked	Analog	No
6503	2126.52	250V 500V 1000V	1 to 500MΩ 1 to 500MΩ 10 to 5000MΩ	—	—	—	0 to 600VAc	Hand-cranked	Analog	No
6505	2130.18	500V 1000V 2500V 5000V	30kΩ to 2000GΩ 100kΩ to 4000GΩ 100kΩ to 10,000GΩ 300kΩ to 10,000GΩ	—	—	0.005 to 49.99μF	2500VAc 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	No
6522	2155.51	250V 500V 1000V	50kΩ to 40GΩ	—	10Ω	—	700VAc/dc	6 x AA Alkaline Batteries	Digital/ Analog	No
6524	2155.52	50V 100V 250V 500V 1000V	10kΩ to 200GΩ	1000kΩ	10Ω, 100Ω	—	700VAc/dc	6 x AA Alkaline Batteries	Digital/ Analog	No
6526	2155.53	50V 100V 250V 500V 1000V	10kΩ to 200GΩ	1000kΩ	10Ω, 100Ω	0.1n to 10μF	700VAc/dc	6 x AA Alkaline Batteries	Digital/ Analog	Yes
6527	2126.53	250V 500V 1000V	1kΩ to 4GΩ 1kΩ to 4GΩ 1kΩ to 4GΩ	0.0 to 400.0kΩ	0.00 to 400Ω	—	0 to 600VAc 0 to 1000Vdc	6 x AA Alkaline Batteries	Digital/ Analog	No
6532	2155.54	50V 100V	10kΩ to 20GΩ	1000kΩ	10Ω, 100Ω	0.1n to 10μF	700VAc/dc	6 x AA Alkaline Batteries	Digital/ Analog	Yes
6534	2155.55	10V 25V 100V 250V 500V	2kΩ to 50GΩ	1000kΩ	10Ω, 100Ω	—	700VAc/dc	6 x AA Alkaline Batteries	Digital/ Analog	Yes
6536	2155.56	10V 100V	2kΩ to 20GΩ	1000kΩ	10Ω, 100Ω	—	700VAc/dc	6 x AA Alkaline Batteries	Digital/ Analog	No
6536 ESD Floor Kit	2155.57	10V 100V	2kΩ to 20GΩ	1000kΩ	10Ω, 100Ω	—	700VAc/dc	6 x AA Alkaline Batteries	Digital/ Analog	No
6550	2130.31	500V 1000V 2500V 5000V 10,000V	10kΩ to 2000GΩ 10kΩ to 4000GΩ 10kΩ to 10,000GΩ 10kΩ to 15,000GΩ 10kΩ to 25,000GΩ	—	—	0.001 to 9.999μF 10.00 to 49.99μF	0 to 2500VAc 0 to 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	Yes
6555	2130.32	500V 1000V 2500V 5000V 10,000V 15,000V	10kΩ to 2000GΩ 10kΩ to 4000GΩ 10kΩ to 10,000GΩ 10kΩ to 15,000GΩ 10kΩ to 25,000GΩ 10kΩ to 30,000GΩ	—	—	0.001 to 9.999μF 10.00 to 49.99μF	0 to 2500VAc 0 to 4000Vdc	Rechargeable NiMH Battery	Digital/ Analog	Yes