

# Crimp socket 1,5 mm, machined 7.010.901.502

|                                     |                                     |
|-------------------------------------|-------------------------------------|
| <b>characteristic of connection</b> | Crimp                               |
| <b>Crimp contact</b>                | Crimp socket Signal, 1,5 mm         |
| <b>Crimp diameter</b>               | 1.5 mm                              |
| <b>Crimp Range</b>                  | 0,56 - 1 mm <sup>2</sup>            |
| <b>Insert</b>                       | sockets                             |
| <b>Kontakt Material</b>             | Copper-Zinc alloy                   |
| <b>Kontakt-Oberfläche Material</b>  | Nickel plated, Gold plated (0,25µm) |
| <b>Mating cycles</b>                | > 1000                              |

Crimp Tool Setting for HUMMEL Crimp Contacts (Crimp Tool 7.000.900.904 or 7.000.900.901)

**REQUEST 3D DATA**

**Certificates**

**ADD TO WATCHLIST**

**PRINT**

SUPPORT

**ELECTRIC COMPONENTS**

- Circular Connectors
- Industrial Cable Glands
- Industrial Ex Cable Glands
- "Hazardous Areas" Cable Glands
- Conduit Systems
- Customized Projects

**HEATING EQUIPMENT**

- Problem Fixer
- Fittings
- Designtechnik
- Accessories, Spare Parts, Tools

**INFORMATION**

- News
- Imprint
- Privacy Policy
- GTC

**NEWSLETTER**

**SUBSCRIBE TO NEWSLETTER**