Description

Magnecraft[™] General Purpose Relays 784 Series

4PDT 15 A

Description



UL listed when used with proper Magnecraft[™] sockets





784 Clear Cover


784 Full-Feature Cover

The 784 Series plug-in relays offer clear or full-feature covers with multiple mounting
options and accessories.

Feature	Benefit
15 A max. switching current	Ideal for automation panels & controls
Clear or full-feature cover options	Full-feature covers include LED indicator & locking test button
4PDT contact configuration	Simultaneously control up to 4 separate circuits
Socket mount option	Simplifies installation & maintenance while also allowing the use of protection modules, hold-down clips & other accessories
Gold-flashed contacts	Reduces contact oxidation & increases shelf life
Mechanical flag indicator	Standard feature displays relay status during testing or operation

Contact Rating	Contact Configuration	Nominal Voltage	Coil Resistance (Ω)	Standard Part Number: Clear Cover	Standard Part Number: Full-Feature
	4PDT	24 Vac 50/60 Hz	84.5	784XDXC-24A	784XDXM4L-24A
15 A		120 Vac 50/60 Hz	2220	784XDXC-120A	784XDXM4L-120A
15 A		12 Vdc	96	-	784XDXM4L-12D
		24 Vdc	388	784XDXC-24D	784XDXM4L-24D





*Please note that LED-only versions are also available. Please contact Customer Service for more information (847-441-2540).



Magnecraft[™] General Purpose Relays

784 Series 4PDT 15 A

Specifications (UL 508)

Part Number	784XDX			
Contact Characteristics				
Terminal Style	Blade			
Contact Configuration	4PDT			
Maximum Current	15 A			
Contact Materials	Silver Alloy			
Maximum Switching Voltage	300 V			
Rated Switching Current at Voltage Resistive: 12 A at 277 Vac 50/60 Hz; 15 A at 120 Vac 50/6 Motor: 1/2 hp at 120 Vac 50/60 Hz; 3/4 hp at 250 Vac 50/6 Pilot Duty: B300				
Minimum Switching Requirement	100 mA at 5 Vdc (0.5 W)			
Coil Characteristics				
Maximum Operating Voltage	110% (AC / DC)			
Maximum Pickup Voltage	85% (AC); 80% (DC)			
Drop-out Voltage Threshold	15% (AC); 10% (DC)			
Average Consumption	2.0 VA (AC); 1.5 W (DC)			
General Characteristics				
Electrical Life at Rated Load	200,000 operations			
Mechanical Life (Unpowered)	10,000,000 operations			
Operating Time (Response Time)	20 ms			
Dielectric Strength - Between Coil and Contact (AC)	2500 V(rms)			
Dielectric Strength - Between Poles (AC)	2500 V(rms)			
Ambient Air Temperature around the Device - Storage	-40 – +85 °C (-40 – +185 °F)			
Ambient Air Temperature around the Device - Operation	-40 - +55 °C (-40 - +131 °F)			
Vibration Resistance - Operational	3 g-n at 10-55 Hz			
Shock Resistance	10 g-n			
Degree of Protection	IP 40			
Weight	80 g (2.82 oz)			
Agency Approvals	UL with socket, UR (E43641), CE, CSA (LR40787), RoHS			


Note: Actual product performance may vary depending on application and environmental conditions.

Magnecraft[™] General Purpose Relays


784 Series 4PDT 15 A


Dimensions — inches (millimeters)

Clear Cover Dimensions




Full-Feature Cover Dimensions





Wiring Diagram







Magnecraft[™] General Purpose Relays 784 Series Accessories



Description

Optional sockets offer customizable, finger-safe[™] solutions including protection modules, hold-down clips, and ID tags. Sockets are DIN rail and panel mount compatible.

Relay Accessories

Description	Function	For Use With Relays	Pkg. Min.	Standard Part Number
Socket 1	Finger-safe, DIN/Panel mount with screw terminals & clamping plates	784	10	70-784D14-1
Adapter 2	DIN rail adapter	784	10	16-784C
Adapter 3	Flange mount adapter	784	10	16-784C1

Socket Accessories







Description	Function	For Use With Socket	Coil Voltage	Pkg. Min.	Standard Part Number
Metal Spring Clip	Secures relay in socket		_	10	16-784SC
Plastic ID Hold-Down Clip 2	Secures relay in socket and provides labeling	70-784D14-1	-	10	16-784IDC
Extruded Aluminum DIN Rail, 39.37" (1000 mm) 3	Quick installation and removal of sockets		-	10	16-700DIN
DIN Rail End Clip 3	Holds sockets firmly in place on DIN rail	-	-	10	16-DCLIP-1
Large Socket Module	MOV Suppressor (Protects from damaging electrical spikes)		24 Vac/Vdc	10	70-ASMM-24
Large Socket Module	Protection Diode (Protects external drive circuitry from inductive voltages)	70-784D14-1	120 Vac/Vdc	10	70-ASMD-250
Large Socket Module	LED Indicator (<i>Provides</i> coil status at a glance)		110/240 Vac/Vdc	10	70-ASMLG-110/240
Large Socket Module	RC Suppressor (Snubs back EMF of relay coil)		110/240 Vac/Vdc	10	70-ASMR-110/240

Note: Use of LED or RC socket module may increase coil power draw by up to 10%.

