Note: This datasheet may be out of date

Please download the latest datasheet of BLM18DN601SN1# from the official website of Murata Manufacturing

Co., Ltd

https://www.murata.com/en-eu/products/productdetail?partno=BLM18DN601SN1%23

### BLM18DN601SN1#

"#" indicates a package specification code.








< List of part numbers with package codes >

BLM18DN601SN1D BLM18DN601SN1J BLM18DN601SN1B



### Appearance & Shape







# **Applications**

Other Usage For general



### Packaging Information

Packaging	Specifications	Minimum Order Quantity
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000
В	Bulk(Bag)	1000



Chip ferrite beads for high frequency noise suppression over a wide frequency range.

#### Features

- 1. High impedance characteristic in 1GHz or higher frequency
- 2. High impedance characteristic over a wide frequency band range of 100MHz to 6GHz
- 3. Low DC Resistance enables large Rated Current

### **Applications**

- Noise suppression for PCs with high-speed CPU and high-speed bus, and for interface lines of peripheral equipment.
- High harmonic noise suppression for digital equipment with several hundred MHz or higher clock speeds
- 3. Prevention of erroneous operation caused by local oscillation signals in mobile phone and W-LAN module (ensuring self-immunity).
- 4. Bias Tee modules in optical transceivers

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated : 2019/08/30




### $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM18DN601SN1\# \ from \ the \ official \ website \ of \ Murata \ Manufacturing} }$ Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=BLM18DN601SN1%23

# BLM18DN601SN1#

"#" indicates a package specification code.

Note: This datasheet may be out of date



Shape	SMD
Size Code (in mm)	1608
Size Code (in inch)	0603
Length	1.6mm
Length Tolerance	±0.15mm
Width	0.8mm
Width Tolerance	±0.15mm
Thickness	0.8mm
Thickness Tolerance	±0.15mm
Impedance (at 100MHz)	600Ω
Impedance (at 100MHz) Tolerance	±25%
Impedance (at 1GHz)	1500Ω
Impedance (at 1GHz) Tolerance	±30%
Rated Current (at 85°C)	700mA
Rated Current (at 125°C)	450mA
DC Resistance(max.)	0.435Ω
Operating Temperature Range	-55°C to 125°C

Mass(typ.)	0.004g
Number of Circuit	1

2 of 3

### Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/08/30


<sup>1.</sup> This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

https://www.murata.com/en-eu/products/productdetail?partno=BLM18DN601SN1%23

## BLM18DN601SN1#

"#" indicates a package specification code.







In operating temperature exceeding +85°C, derating of current is necessary for this series.

Please apply the derating curve shown in chart according to the operating temperature.

Derating of Rated Current



Impedance-Frequency Characteristics



**Derating of Rated Current** 

**Equivalent Circuit** 

3 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/