Note: This datasheet may be out of date Please download the latest datasheet of DXW21BN7511T#from the official website of Murata Manufacturing

DXW21BN7511T#

"#" indicates a package specification code.







< List of part numbers with package codes > DXW21BN7511TL DXW21BN7511TK DXW21BN7511TB




Appearance & Shape



Packaging Information





| Packaging | Specifications | Minimum Order Quantity |
|-----------|---------------------|---------------------------|
| L | 180mm Embossed Tape | 2000 |
| К | 330mm Embossed Tape | 10000 |
| В | Bulk(Bag) | 500 |



| Other Usage | Fo |
|-------------|----|
|-------------|----|

r general

1 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Note: This datasheet may be out of date.

Please download the latest datasheet of DXW21BN7511T#from the official website of Murata Manufacturing Co., Ltd.

DXW21BN7511T#

"#" indicates a package specification code.



- 1. Ultra Miniature Wire Wound Transformer (2.0×1.2×1.2mm)
- 2. Low Insertion Loss
- 3. Wideband Frequency Range
- 4. Surface Mount

Applications

TV tuners, Cable TV tuners and Communication application that require unbalance mode to balance mode conversion.

2 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



DXW21BN7511T#

"#" indicates a package specification code.



| Operating Temperature Range | -40°C to 85°C |
|-----------------------------|--|
| Frequency Range | 50MHz to 1200MHz |
| Insertion Loss | 50 to 870MHz:1.0dB max.(at Freq. Range),870 to 1200MHz:1.2dB max.(at Freq. Range) |
| Size Code (in mm) | 2012 |
| Size Code (in inch) | 0805 |
| Length | 2mm |
| Length Tolerance | ±0.2mm |
| Width | 1.2mm |
| Width Tolerance | ±0.2mm |
| Thickness | 1.2mm |
| Thickness Tolerance | ±0.2mm |
| Power Rating | 27dBm |
| Rated Voltage | 20Vdc |
| Withstanding Voltage | 50Vdc |
| Port Impedance | 75Ω - 75Ω |
| CMRR(min.) | 20dB |
| DC Resistance(max.) | 0.77Ω |
| Insulation Resistance(min.) | 10ΜΩ |
| Mass(typ.) | 0.011g |

3 of 4

Attention

1.This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





muRata URL : https://www.murata.com/

DXW21BN7511T#

"#" indicates a package specification code.








Insertion Loss Characteristics

CMRR Characteristics



Equivalent Circuit

4 of 4

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

