This announcement is based on product catalogue information previously shown before its discontinuation.

Product information of the existing product may be different from this version.

# **MOS FET Relays**

G3VM-354C/C1/F/F1

# Analog-switching MOS FET Relays with DPST-NC Contact.

## General-purpose Models Added.

- Switches minute analog signals.
- Switching AC and DC.
- General-purpose models (models with high ON resistance) added to the series.

#### **RoHS** compliant

Refer to "Common Precautions".

## ■ Application Examples

- Electronic automatic exchange systems
- · Security systems
- Datacom (modem) systems
- FA systems
- Measurement devices







*9*1

**Note:** The actual product is marked differently from the image shown here.

#### **■**List of Models


Contact form	Terminals	Load voltage (peak value)	Model	Number per stick	Number per tape
DPST-NC	PCB terminals	350 VAC	G3VM-354C	50	
			G3VM-354C1		
Surface-mounting termi-			G3VM-354F		
	als		G3VM-354F1		
			G3VM-354F(TR)		1,500
			G3VM-354F1(TR)		

#### ■ Dimensions


Note: All units are in millimeters unless otherwise indicated.









1.2±0.15 0.5±0.1 2.54±0.25 W



G3VM-354F/F1









# ■ Terminal Arrangement/Internal Connections (Top View)

G3VM-354C/C1




G3VM-354F/F1



### **■ PCB Dimensions (Bottom View)**

G3VM-354C/C1



# ■ Actual Mounting Pad Dimensions (Recommended Value, Top View)

Note:

Product information of the existing product may be different from this version.

# ■ Absolute Maximum Ratings (Ta = 25°C)

Item		Symbol Rating		Unit	Measurement Conditions		
Input	LED forward current	I <sub>F</sub>	50	mA			
	Repetitive peak LED forward current	I <sub>FP</sub>	1	Α	100 μs pulses, 100 pps		
	LED forward current reduction rate	Δ I <sub>F</sub> /°C	-0.5	mA/°C	Ta≥25°C		
	LED reverse voltage	$V_R$	5	V			
	Connection temperature	Tj	125	°C			
Output	Output dielectric strength	V <sub>OFF</sub>	350	V			
	Continuous load current	I <sub>O</sub>	150 (100)	mA			
	ON current reduction rate	∆ I <sub>ON</sub> /°C	-1.5 (-1)	mA/°C	Ta ≥ 25°C		
	Connection temperature	Tj	125	°C			
Dielectric strength between input and output (See note 1.)		V <sub>I-O</sub>	2,500	Vrms	AC for 1 min		
Operating temperature		Ta	-40 to +85	°C	With no icing or condensat		
Storage temperature		T <sub>stg</sub>	-55 to +125	°C	With no icing or condensation		
Soldering temperature (10 s)			260	°C	10 s		

 The dielectric strength between the input and output was checked by applying voltage between all pins as a group on the LED side and all pins as a group on the light-receiving side.


C1/F/F1

Values in parentheses are for the G3VM-354C1/F1.

### **■** Electrical Characteristics (Ta = 25°C)

Item		Symbol	Mini- mum	Typical	Maxi- mum	Unit	Measurement conditions
Input	LED forward voltage	$V_{F}$	1.0	1.15	1.3	V	I <sub>F</sub> = 10 mA
	Reverse current	I <sub>R</sub>			10	μΑ	V <sub>R</sub> = 5 V
	Capacity between terminals	C <sub>T</sub>		30		pF	V = 0, f = 1 MHz
	Trigger LED forward current	I <sub>FT</sub>		1	3	mA	I <sub>OFF</sub> = 10 μA
Output	Maximum resistance with output ON	R <sub>ON</sub>		15 (30)	25 (50)	Ω	I <sub>O</sub> = 150 mA
	Current leakage when the relay is open	I <sub>LEAK</sub>			1.0	μΑ	I <sub>F</sub> = 5 mA, V <sub>OFF</sub> = 350 V
Capacity between I/O terminals		C <sub>I-O</sub>		0.8		pF	f = 1 MHz, Vs = 0 V
Insulation resistance		R <sub>I-O</sub>	1,000			ΜΩ	V <sub>I-O</sub> = 500 VDC, RoH ≤ 60%
Turn-ON time		tON		0.1 (0.25)	1.0 (0.5)	ms	$I_F$ = 5 mA, $R_L$ = 200 Ω, $V_{DD}$ = 20 V (See note 2.)
Turn-OFF time		tOFF		1.0 (0.5)	3.0 (1)	ms	

Note: 2. Turn-ON and Turn-OFF Times



Values in parentheses are for the G3VM-354C1/F1.

# **■**Recommended Operating Conditions

Use the G3VM under the following conditions so that the Relay will operate properly.


Item	Symbol	Minimum	Typical	Maximum	Unit
Output dielectric strength	$V_{DD}$			280	V
Operating LED forward current	IF	5		25	mA
Continuous load current	Io			150 (100)	mA
Operating temperature	Ta	- 20		65	°C

Values in parentheses are for the G3VM-354C1/F1.

### **■** Engineering Data

#### Load Current vs. Ambient Temperature

G3VM-354C(F) G3VM-354C1/F1



# **■** Safety Precautions

Refer to "Common Precautions" for all G3VM models.