TABLE 1

PART NO.	n	A	B
HKP-2FSA01	2	2.54	5.08
HKP-3FSA01	3	5.08	7.62
HKP-4FSA01	4	7.62	10.16
HKP-5FSA01	5	10.16	12.70
HKP-6FSA01	6	12.70	15.24
HKP-7FSA01	7	15.24	17.78
HKP-8FSA01	8	17.78	20.32
HKP-9FSA01	9	20.32	22.86
HKP-10FSA01	10	22.86	25.40
HKP-11FSA01	11	25.40	27.94
HKP-12FSA01	12	27.94	30.48
HKP-13FSA01	13	30.48	33.02
HKP-14FSA01	14	33.02	35.56
HKP-15FSA01	15	35.56	38.10
HKP-16FSA01	16	38.10	40.64
HKP-17FSA01	17	40.64	43.18
HKP-18FSA01	18	43.18	45.72
HKP-19FSA01	19	45.72	48.26
HKP-20FSA01	20	48.26	50.80
HKP-21FSA01	21	50.80	53.34
HKP-22FSA01	22	53.34	55.88
HKP-23FSA01	23	55.88	58.42
HKP-24FSA01	24	58.42	60.96
HKP-25FSA01	25	60.96	63.50
HKP-26FSA01	26	63.50	66.04
HKP-27FSA01	27	66.04	68.58
HKP-28FSA01	28	68.58	71.12
HKP-29FSA01	29	71.12	73.66
HKP-30FSA01	30	73.66	76.20
HKP-31FSA01	31	76.20	78.74
HKP-32FSA01	32	78.74	81.28
HKP-33FSA01	33	81.28	83.82
HKP-34FSA01	34	83.82	86.36
HKP-35FSA01	35	86.36	88.90
HKP-36FSA01	36	88.90	91.44
HKP-37FSA01	37	91.44	93.98
HKP-38FSA01	38	93.98	96.52
HKP-39FSA01	39	96.52	99.06
HKP-40FSA01	40	99.06	101.60
HKP-41FSA01	41	101.60	104.14
HKP-42FSA01	42	104.14	106.68
HKP-43FSA01	43	106.68	109.22
HKP-44FSA01	44	109.22	111.76
HKP-45FSA01	45	111.76	114.30
HKP-46FSA01	46	114.30	116.84
HKP-47FSA01	47	116.84	119.38
HKP-48FSA01	48	119.38	121.92
HKP-49FSA01	49	121.92	124.46
HKP-50FSA01	50	124.46	127.00



NOTE1. "n" SHOWS NUMBER OF CONTACTS.

2. APPLICABLE CONTACT
- HKP-F5 ( ) ( )
- HKP-F7 ( ) ( )

3									
2									
1				1	INSULATOR	PPO	1	———	UL94V-0 BLACK
LTR.	DATE	BY	REV. DESCRIPT	No.	PART NAME	MATERIAL	QTY	FINISH	NOTE

DATE JAN.10 (2002)	SCALE 10/1	UNIT mm (INCH)	3RD. A. P	HONDA TSUSHIN KOGYO CO., LTD.
APP. DATE&REV.				
DR.	DE.	CHK.	CHK.	APP.
K.NISHIMAE	K.NISHIMAE	—	—	H.EBIHARA

NAME	INSULATOR	
PART NO.	HKP-( )FSA01	REV.

HONDA TSUSHIN KOGYO CO., LTD.
The product information in this data is for reference only.
Please contact our sales staff for further information before considering or
designing any of our products.
Please use the most current and accurate
Engineering Drawing for the most

ID= HKP-@FSA01 E0