

Product Search Data Sheet

Note: This datasheet may be out of date. Please download the latest datasheet of LQW18CA85NJ00# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=LQW18CA85NJ00%23

"#" indicates a package specification code.

LQW18CA85NJ00#


0603(inch) size wound ferrite core inductor for audio line choke.



< List of part numbers with package codes > LQW18CA85NJ00B LQW18CA85NJ00J LQW18CA85NJ00D

Appearance & Shape





References

Packaging	Specifications	Standard Packing Quantity
В	Bulk(Bag)	500
J	330mm Paper Tape	10000
D	180mm Paper Tape	4000

Mass (typ.)		
1 piece	0.004g	

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Rata Product Search Data Sheet

LQW18CA85NJ00#

Note: This datasheet may be out of date. Please download the latest datasheet of LQW18CA85NJ00# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=LQW18CA85NJ00%23

"#" indicates a package specification code.



Specifications

L size	1.6±0.15mm
W size	0.8±0.15mm
T size	0.8±0.15mm
Size code inch (mm)	0603 (1608)
Inductance	85nH±5%
Inductance Test Frequency	10MHz
Rated current (Itemp) (Based on Temperature rise)	1650mA
Max. of DC resistance	0.048Ω
Class of magnetic shield	No Shield
Self resonance frequency (min.)	1800MHz
Operating Temperature Range(Self-temperature rise is not included)	-40℃ to 85℃
Series	LQW18CA_00

2 of 3



1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





Product Search Data Sheet

Note: This datasheet may be out of date. Please download the latest datasheet of LQW18CA85NJ00# from the official website of Murata Manufacturing Co., Ltd.


http://www.murata.com/en/products/productdetail?partno=LQW18CA85NJ00%23


"#" indicates a package specification code.

LQW18CA85NJ00#

Characteristic Data

The charts below may show another part number which shares its characteristics.





Frequency Characteristic (Z) 800 700 mpedance [ohm] 600 500 400 300 200 100 0 100M 1G 10M 10G Frequency [Hz] LQW18CA85NJ00 Z

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued

without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

