


Inductor - Axial

multicomp PRO

**RoHS
Compliant**



Diagram



Part Number Table

Description	L μH	Q (Min.)	Test Freq. MHz	SRF (MHz) (Min.)	DCR (OHM) (Max.)	Rated DC Current (mA) (Max.)	Colour Code				Part Number
							1st	2nd	3rd	4th	
Inductor, Choke Axial, 1.5μH, 0.83A	1.5	55	7.96	131	0.23	830	Bn	Gn	Gd	S	MCAL0410A1-1R5KU
Inductor, Choke Axial, 10μH, 0.5A	10	85	7.96	45	0.58	500	Bn	Bk			MCAL0410A1-100KU
Inductor, Choke Axial, 22μH, 0.41A	22	65	2.52	9.9	0.84	410	R	R	Bk		MCAL0410A1-220KU
Inductor, Choke Axial, 33μH, 0.37A	33	55	2.52	6.3	1.03	370	0	0			MCAL0410A1-330KU
Inductor, Choke Axial, 100μH, 0.275A	100	30	2.52	4.8	1.8	275	Bn	Bk	Bn		MCAL0410A1-101KU
Inductor, Choke Axial, 470μH, 0.34A	470	60	0.796	2.25	7.7	126	Y	V	Bn		MCAL0410A1-471KU

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro
Farnell.com/multicomp-pro
Element14.com/multicomp-pro

multicomp PRO