

# Digital Thickness Gauge

**multicomp** PRO

**RoHS  
Compliant**




## Features

- Made of extra strong carbon fibre composites
- Light weight and durable to use
- 8mm LCD display
- Suited for measuring thickness of paper, film, wire, sheet jewellery, leather etc.

## Specifications

Measuring Range	: 0 to 12mm (0.5")
Resolution	: 0.01mm (0.0005")
Accuracy	: $\pm 0.03$ mm (0.0015")
Operating Temperature	: 0°C to +40°C
Storage Temperature	: -20°C to +70°C
Influence of Humidity	: $\leq 80\%$
Throat Depth	: 19mm (0.75")
Battery	: 1.5V (SR44)

## Diagram



1.	Frame
2.	Contact Point
3.	Anvil
4.	Battery Cap
5.	Zero Setting

6.	Power off
7.	LCD display
8.	Lever
9.	mm/in change and power on

## Operating the Gauge

1. While closing the measuring face (2 and 3), press the power on with (9), "0.00" will be display on the display panel (7).
2. Press the lever (8) to open the measuring face. Insert the work piece between the measuring face, and release the lever. The contact point is pressed against the work piece under the spring force. When the displayed value is stable, take measurements.
3. Press the power off switch (6) and turn off the power.

## Part Number Table

Description	Part Number
Digital Thickness Gauge, 0 to 12mm (0.5") vs 0mm to 12.7mm (0.5"), $\pm 0.01$ mm	MP700108

**Important Notice** : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro  
Farnell.com/multicomp-pro  
Element14.com/multicomp-pro

**multicomp** PRO