



RDC40: Compatible with multi-rotational position tracking.

RDC50: Compact, high precision, high heat resistant rotary sensors meet various needs in position detection.

Magnetic Sensors Piezo Sensors Capacitive Sensor

Resistive Sensors



Typical Specifications


Items	Specifications			
Items	RDC40	RDC50		
Operating life	100,000cycles	1,000,000cycles		
Total resistance	10kΩ			
Operating temperature range	-30°C to +80°C	-40°C to +120°C		

Product List

Mounting method	Effective variable range	Linearity	Hollow shaft variation	Operating life (cycles)	Minimum order unit (pcs.)	Model No.	Drawing No.
Connector type	13rotations	±1%	_	100,000	770	RDC401D07A	1
Horizontal type	320°	±2%	φ3.5 dia	1,000,000	3,000	RDC501015A	2
			ϕ 3.5 dia with radius			RDC501011A	3
Vertical type			φ3.5 dia		1,600	RDC502010A	4
Reflow type	320			1,000,000	3,900	RDC503013A	5
			ϕ 3.5 dia with radius			RDC503015A	6
Reflow type (Low-profile)			φ4 dia		3,600	RDC506002A	7

Packing Specifications

Tray/Taping Unit:mm



Series	Packing Specifications	Number of pa	ckages (pcs.)	Tape width	Export package measurements (mm)	
		1 case /Japan	1 case /export packing	(mm)		
RDC40	Tray	770	770	_	526×370×191	
RDC501		1,500	3,000			
RDC502		1,600	1,600		370×280×92	
RDC503	Taping	3,900	3,900	24	407×415×135	
RDC506		3,600	3,600			

Notes


- 1. Additional product specifications in response to those not included in the above recommended products are also available.
- 2. Please place purchase orders per minimum order unit N (integer).



Magnetic Sensors Piezo Sensors Capacitive Sensor

Resistive

Sensors







■ Dimensions Unit:mm

Magnetic Sensors Piezo Sensors Capacitive

Sensor Resistive Sensors









Index for Functions

Туре		Rotary Type			Linear Type		
Series		RDC40	RDC50	RDC80	RDC10	%RD7	
Photo							
Travel (mm)		_		_	14mm (RDC1014) 22mm (RDC1022) 32mm (RDC1032) 47mm (RDC1047)	8mm (RD708) 9mm (RD709) 12mm (RD712)	
Mounting method						Vertical Horizontal	
Effectiv	e variable angle	4680 (13 rotations)	320	330 (1-phase) 360 (2-phase)			
Soldering	Manual soldering			350°C ma	ax. 3s max.		
	Dip soldering		260℃, 4±1s			260°C, 4±1s	
	Re-flow soldering		Please see P.522				
Operating temperature range		-30°C to +80°C	-40°C to +120°C		-30°C to +85°C	-40°C to +105°C	
Automotive use		•	•	•		•	
Machanical Rotational torque		_			0.25N max.	2N max.	
anical mance	Rotational torque	2mN∙r	2mN·m max. 10mN·m max.				
per	Total resistance tolerance	±30%			±20%		
Electrical performance	Linearity (%)	±1	±2	±3	±0.5	±1	
cal	Rated Voltage (VDC)	5				12	
Environmental test	Cold	-30±3°C for 240h	-40±3°C for 168h		-40±3°C for 240h	-40±3°C for 96h	
	Dry heat	80±2°C for 240h	120±3℃ for 168h		90±2°C for 240h	105±2℃ for 96h	
ental	Damp heat	60±2℃, 90 to 95%RH for 240h	60±2°C, 40h 90 to 95%RH for 96h		60±2℃, 90 to 95%RH for 240h	40±2℃, 90 to 95%RH for 96h	
Page		51	513 516		517	519	

Resistive Sensors Product Specifications
 Resistive Sensors Soldering Conditions
 Resistive Sensors Measurement and Test Methods
 Resistive Sensors Caution

Note

- 1. %The RD7 series are used to detect vehicle headlight angles.
- 2. •marks in "Available for automotive use" indicate that all of the series products can work at the operating temperature range from -40°C to +85°C.

Magnetic Sensors

Piezo Sensors

Capacitive Sensor

Resistive Sensors

Product Specifications


■ Method for Regulating the Linearity


Magnetic Sensors


Piezo Sensors

Capacitive Sensor


Resistive Sensors







Model RDC10/RD7 With rated voltage applied between terminals 1 and 3, the straight line which connects the measured output values VB and VA at specified reference positions B and A is assumed to be an ideal straight line, so that deviation against the ideal straight line when the voltage applied between terminals 1 and 3 is assumed to be 100% can be expressed as a percentage.






Soldering Conditions

Soldering Conditions

1. Recommended reflow conditions



Piezo Sensors Capacitive

Magnetic Sensors

Capacitive Sensor

Resistive Sensors

- 2. Cleaning Cleaning should not be attempted.
- 3. Type of solder to be used Use cream solder that contains 10 15 %wt flux.
- 4. Number of solder applications apply solder only once

Notes

- 1. When using an infrared reflow oven, solder may not always be applied as intended. Be sure to use a hot air reflow oven or a type that uses infrared rays in combination with hot air.
- 2. The temperatures given above are the maximum temperatures at the terminals of the potentiometer when employing a hot air reflow method. The temperature of the PC board and the surface temperature of the potentiometer may vary greatly depending on the PC board material, its size and thickness. Ensure that the surface temperature of the potentiometer does not rise to 250°C or greater.
- 3. Conditions vary to some extent depending on the type of reflow bath used. Be sure to give due consideration to this prior to use.

Measurement and Test Methods

Analog Output Contact Type Sensor _

[Total Resistance]

The total resistance, with the shaft (lever) placed at the end of terminal 1 or 3, shall be determined by measuring the resistance between the resistor terminals 1 and 3 unless otherwise specified.

(Rating Voltage)

The rating voltage corresponding to the rated power shall be determined by the following equation. When the resulting rated voltage exceeds the maximum operating voltage of a specific resistor, the maximum operating voltage shall be taken as the rated voltage.

 $E=\sqrt{P \cdot R}$ $E: Rated \ voltage \ (V)$ $P: Rated \ power \ (W)$ $R: Total \ nominal \ resistance \ (\Omega)$