# RM22UA31MR

Voltage control relay 50mV...5Vac/dc, 2 C/O





### Main

Range of product	Zelio Control	
Product or component type	Modular measurement and control relays	
Relay type	Voltage control relay	
Network number of phases	1 phase	
Supply circuit type	DC	
Relay name	RM22UA	
Relay monitored parameters	Overvoltage or undervoltage detection Undervoltage and overvoltage in window mode	
Time delay type	Adjustable 0.130 s, +/- 10 % of the full scale value on crossing the threshold Tt	
Switching capacity in VA	2000 VA	
Measurement range	50 mV5 V voltage AC/DC 50/60 Hz	

# Complementary

Oompicincinal y		
Reset time	<= 1500 ms at maximum voltage	
Maximum switching voltage	250 V AC	
Minimum switching current	10 mA at 5 V DC	
Maximum switching current	8 A AC	
[Us] rated supply voltage	24240 V AC/DC, 50/60 Hz	
Supply voltage limits	20.4264 V AC/DC	
Power consumption in VA	3.5 VA AC	
Power consumption in W	1.5 W DC	
Supply frequency	4070 Hz +/- 10 %	
Resistance across terminals	30 kOhm at E2-M terminals 5 kOhm at E1-M terminals 50 kOhm at E3-M terminals	
Output contacts	2 C/O	
Nominal output current	8 A	
Hysteresis	3 % fixed of full scale for window mode 550 % adjustable of threshold setting for overvoltage or undervoltage detection	
Run-up delay at power-up	<= 600 ms	
Measuring cycle	100 ms measurement cycle as true rms value	
Repeat accuracy	+/- 0.5 % input and measurement circuit +/- 2 % time delay	
Measurement error	< 1 % over the whole range with voltage variation 0.05 %/°C with temperature variation	
Response time	<= 500 ms	
Overvoltage category	III conforming to IEC 60664-1	
Insulation resistance	> 100 MOhm at 500 V DC conforming to IEC 60255-27	
Insulation	Between supply and measurement	
Mounting position	Any position	
Connections - terminals	Screw terminals 2 x 0.52 x 2.5 mm² - AWG 20AWG 14, solid cable without cable end Screw terminals 2 x 0.22 x 1.5 mm² - AWG 24AWG 16, flexible cable with cable end Screw terminals 1 x 0.51 x 3.3 mm² - AWG 20AWG 12, solid cable without cable end Screw terminals 1 x 0.21 x 2.5 mm² - AWG 24AWG 14, flexible cable with cable end	
Tightening torque	0.61 N.m conforming to IEC 60947-1	
Housing material	Self-extinguishing plastic	

Status LED	LED yellow for relay ON LED green for power ON	
Mounting support	35 mm DIN rail conforming to EN/IEC 60715	
Electrical durability	100000 cycles	
Mechanical durability	10000000 cycles	
Utilisation category	AC-15 conforming to IEC 60947-5-1 DC-13 conforming to IEC 60947-5-1 AC-1 conforming to IEC 60947-4-1 DC-1 conforming to IEC 60947-4-1	
Safety reliability data	MTTFd = 308.2 years B10d = 290000	
Contacts material	Cadmium free	
Width	22.5 mm	
Product weight	0.11 kg	

## **Environment**

immunity to microbreaks	10 ms	
electromagnetic compatibility	Emission standard for industrial environments conforming to EN/IEC 61000-6-4 Emission standard for residential, commercial and light-industrial environments conforming to EN/IEC 61000-6-3 Immunity for industrial environments conforming to EN/IEC 61000-6-2 Conducted and radiated emissions class B conforming to CISPR 22 Immunity for residential, commercial and light-industrial environments conforming to EN/IEC 61000-6-1 Electrostatic discharge 6 kV level 3 contact discharge conforming to IEC 61000-4-2 Electrostatic discharge 8 kV level 3 air discharge conforming to IEC 61000-4-2 Radiated radio-frequency electromagnetic field immunity test 10 V/m level 3 conforming to IEC 61000-4-3 Electrical fast transient/burst immunity test 4 kV level 4 direct conforming to IEC 61000-4-4 Electrical fast transient/burst immunity test 2 kV level 4 capacitive coupling conforming to IEC 61000-4-4 Surge immunity test 4 kV level 4 common mode conforming to IEC 61000-4-5 Surge immunity test 2 kV level 4 differential mode conforming to IEC 61000-4-5 Conducted and radiated emissions class B group 1 conforming to CISPR 11	
standards	EN/IEC 60255-1	
product certifications	CCC CE CSA GL UL RCM EAC China RoHS	
ambient air temperature for storage	-4070 °C	
ambient air temperature for operation	-2050 °C at 60 Hz -2060 °C at 50 Hz AC/DC	
relative humidity	9397 % at 2555 °C conforming to IEC 60068-2-30	
vibration resistance	0.075 mm (f = 1058.1 Hz) (not in operation) conforming to IEC 60068-2-6 1 gn (f = 1058.1 Hz) (not in operation) conforming to IEC 60068-2-6 0.035 mm (f = 58.1150 Hz) (in operation) conforming to IEC 60068-2-6 0.5 gn (f = 58.1150 Hz) (in operation) conforming to IEC 60068-2-6	
shock resistance	15 gn for 11 ms (not in operation) conforming to IEC 60068-2-27 5 gn for 11 ms (in operation) conforming to IEC 60068-2-27	
IP degree of protection	IP20 on terminals conforming to IEC 60529 IP40 on housing conforming to IEC 60529 IP50 on front panel conforming to IEC 60529	
pollution degree	3 conforming to IEC 60664-1	
	2.5 kV for 1 min AC 50 Hz conforming to IEC 60255-27	

# Offer Sustainability

Sustainable offer status	Green Premium product	
RoHS (date code: YYWW)	Compliant - since 1524 - Schneider Electric declaration of conformity	
REACh	Reference not containing SVHC above the threshold	
Product environmental profile	Available	




### Contractual warranty

Warranty period


18 months

### **Dimensions**



# **Mounting and Clearance**

#### **Rail Mounting**



## **Voltage Measurement Relay**

Wiring Diagram

A1	A2	М
E1	E2	E3
₹ <u<< th=""><th>M 5/4</th><th>#   #</th></u<<>	M 5/4	#   #
12	11	14
22	21	24


A1,A2 : Supply voltage

E1,E2,E3,M: Voltages to be measured 11-14,12: 1st C/O contact of output relay 21-24,22: 2nd C/O contact of output relay

# **Function Diagrams**


### **Undervoltage Control**


Without memory ("No Memory" mode)



### **Overvoltage Control**

Without memory ("No Memory" mode)





#### Legend

Tt Time delay after crossing of threshold

Un Nominal supply voltage

**U** Monitored supply voltage

**H** Hysteresis

U> Overvoltage threshold

U< Undervoltage threshold

11-12/11-14, 21-22/21-24 Output relay connections

Relay status: black color = energized.

**NOTE:** In "Memory" mode, the relay opens when crossing of the threshold is detected and then stays in that position. The power supply voltage must be switched off to reset the product.