

BROADCAST SIGNAL SPLITTERS (Cont.)



Fig. 4

Broadcast Amplifiers

Retail Part No.	Bulk Part No.	Figure Number	Description
SD-4303		4	1-way Amplifier 10dB 5-500 MHz for indoor use

DROP TAPS



Fig. 6



Fig. 7




Fig. 8

Drop Taps

Retail Part No.	Bulk Part No.	Figure Number	Description	Frequency(MHz)	Insertion Loss(dB)max	Isolation Loss(dB)min	Tap Loss(+/-dB)max
32-2006	32-2006-BU	6	Miniature UHF/VHF/FM Droptap(6dB)	5	3.0	23	0.5
				50	2.6	31	0.5
				300	2.5	25	0.5
				500	2.5	27	0.5
				750	3.0	28	0.5
				1000	3.2	27	0.5
32-2009	32-2009-BU	6	Miniature UHF/VHF/FM Droptap(9dB)	5	1.7	30	0.5
				50	1.4	30	0.5
				300	1.3	33	0.5
				500	1.3	33	0.5
				750	1.8	30	1.0
				1000	2.0	28	1.0
32-2012	32-2012-BU	6	Miniature UHF/VHF/FM Droptap(12dB)	5	2.5	36	0.5
				50	0.5	36	0.5
				300	0.5	33	0.5
				500	0.7	30	0.5
				750	1.5	25	0.5
				1000	1.8	23	0.5
	32-3183-BU	7	UHF/VHF/FM Droptap (12dB)	5-1000	N/A	N/A	N/A
SD-592-BU		8	Miniature UHF/VHF/FM Droptap(12dB)	5	2.5	36	0.5
				50	0.5	36	0.5
				300	0.5	33	0.5
				500	0.7	30	0.5
				750	1.5	25	0.5
				1000	1.8	23	0.5