Product datasheet Characteristics

SR2B121BD

compact smart relay Zelio Logic - 12 I O - 24 V DC - clock - display



Main

Dance of seadurat	7-lis Lavia
Range of product	Zelio Logic
Product or component type	Compact smart relay

Complementary

With	:±
0500 with FBD programming 0240 with ladder programming	
690 ms	
10 years at 25 °C	
6 s/month at 25 °C 12 min/year at 055 °C	
Program memory on each power up	ho used for determining suitability or solishility
24 V DC	
19.230 V	
100 mA (without extension)	
3 W without extension	
With	
8 conforming to EN/IEC 61131-2 type 1	The fitting for
Resistive	ď
24 V DC	- to
4 mA	
1 kHz for discrete input	don transfer of the transfer o
>= 15 V for I1IA and IHIR discrete input circuit >= 15 V for IBIG used as discrete input circuit	
e state 0 guaranteed <= 5 V for I1IA and IHIR discrete input circuit <= 5 V for IBIG used as discrete input circuit	
>= 1.2 mA for IBIG used as discrete input circuit >= 2.2 mA for I1IA and IHIR discrete input circuit	ie seine
< 0.5 mA for IBIG used as discrete input circuit	. <u></u>
	0500 with FBD programming 0240 with ladder programming 690 ms 10 years at 25 °C 6 s/month at 25 °C 12 min/year at 055 °C Program memory on each power up 24 V DC 19.230 V 100 mA (without extension) 3 W without extension With 8 conforming to EN/IEC 61131-2 type 1 Resistive 24 V DC 4 mA 1 kHz for discrete input >= 15 V for I1IA and IHIR discrete input circuit >= 15 V for IBIG used as discrete input circuit <= 5 V for IBIG used as discrete input circuit >= 1.2 mA for IBIG used as discrete input circuit >= 2.2 mA for I1IA and IHIR discrete input circuit

	< 0.75 mA for I1IA and IHIR discrete input circuit	
Input compatibility	3-wire proximity sensors PNP (discrete input)	
Analogue input number	4	
Analogue input type	Common mode	
Analogue input range	010 V 024 V	
Maximum permissible voltage	30 V (analogue input circuit)	
Analogue input resolution	8 bits	
LSB value	39 mV (analogue input circuit)	
Conversion time	Smart relay cycle time for analogue input circuit	
Conversion error	+/- 5 % at 25 °C for analogue input circuit +/- 6.2 % at 55 °C for analogue input circuit	
Repeat accuracy	+/- 2 % at 55 °C for analogue input circuit	
Operating distance	10 m between stations, with screened cable (sensor not isolated) for analogue input circuit	
Input impedance	12 kOhm (IBIG used as analogue input circuit) 12 kOhm (IBIG used as discrete input circuit) 7.4 kOhm (I1IA and IHIR discrete input circuit)	
Number of outputs	4 relay output(s)	
Output voltage limits	24250 V AC (relay output) 530 V DC (relay output)	
Contacts type and composition	NO for relay output	
Output thermal current	8 A for all 4 outputs (relay output)	
Electrical durability	500000 cycles AC-12 at 230 V, 1.5 A for relay output conforming to EN/IEC 60947-5-1 500000 cycles AC-15 at 230 V, 0.9 A for relay output conforming to EN/IEC 60947-5-1 500000 cycles DC-12 at 24 V, 1.5 A for relay output conforming to EN/IEC 60947-5-1 500000 cycles DC-13 at 24 V, 0.6 A for relay output conforming to EN/IEC 60947-5-1	
Switching capacity in mA	>= 10 mA at 12 V (relay output)	
Operating rate in Hz	0.1 Hz (at le) for relay output 10 Hz (no load) for relay output	
Mechanical durability	10000000 cycles (relay output)	
[Uimp] rated impulse withstand voltage	4 kV conforming to EN/IEC 60947-1 and EN/IEC 60664-1	
Clock	With	
Response time	10 ms (from state 0 to state 1) for relay output 5 ms (from state 1 to state 0) for relay output	
Connections - terminals	Screw terminals, clamping capacity: 1 x 0.21 x 2.5 mm² AWG 25AWG 14 semi-solid Screw terminals, clamping capacity: 1 x 0.21 x 2.5 mm² AWG 25AWG 14 solid Screw terminals, clamping capacity: 1 x 0.251 x 2.5 mm² AWG 24AWG 14 flexible with cable end Screw terminals, clamping capacity: 2 x 0.22 x 1.5 mm² AWG 24AWG 16 solid Screw terminals, clamping capacity: 2 x 0.252 x 0.75 mm² AWG 24AWG 18 flexible with cable end	
Tightening torque	0.5 N.m	
Overvoltage category	III conforming to EN/IEC 60664-1	
Product weight	0.25 kg	

Environment

Immunity to microbreaks	<= 1 ms		
Product certifications	UL		
	GOST		
	GL		
	C-Tick		
	CSA		
Standards	EN/IEC 61000-4-3		
	EN/IEC 61000-4-11		
	EN/IEC 60068-2-27 Ea		
	EN/IEC 61000-4-6 level 3		
	EN/IEC 61000-4-2 level 3		
	EN/IEC 61000-4-5		
	EN/IEC 60068-2-6 Fc		
	EN/IEC 61000-4-4 level 3		
	EN/IEC 61000-4-12		
IP degree of protection	IP20 (terminal block) conforming to IEC 60529		

	IP40 (front panel) conforming to IEC 60529	
Environmental characteristic	EMC directive conforming to EN/IEC 61000-6-2 EMC directive conforming to EN/IEC 61000-6-3 EMC directive conforming to EN/IEC 61000-6-4 EMC directive conforming to EN/IEC 61131-2 zone B Low voltage directive conforming to EN/IEC 61131-2	
isturbance radiated/conducted Class B conforming to EN 55022-11 group 1		
Pollution degree	2 conforming to EN/IEC 61131-2	
Ambient air temperature for operation	-2040 °C in non-ventilated enclosure conforming to IEC 60068-2-1 and IEC 60068-2-2 -2055 °C conforming to IEC 60068-2-1 and IEC 60068-2-2	
Ambient air temperature for storage	-4070 °C	
Operating altitude	2000 m	
Altitude transport	<= 3048 m	
Relative humidity	95 % without condensation or dripping water	


Contractual warranty

Warranty pariod	10 months	
Warranty period	18 months	

SR2B121BD


Compact and Modular Smart Relays

Mounting on 35 mm/1.38 in. DIN Rail




(1) With SR2USB01 or SR2BTC01

Screw Fixing (Retractable Lugs)




(1) With SR2USB01 or SR2BTC01

Position of Display




Compact and Modular Smart Relays

Connection of Smart Relays on DC Supply



- (1) 1 A quick-blow fuse or circuit-breaker.
- (2) Fuse or circuit-breaker.
- (3) Inductive load.
- (4) Q9 and QA: 5 A (max. current in terminal C: 10 A).

Discrete Input Used for 3-Wire Sensors



(1) 1 A quick-blow fuse or circuit-breaker.

Product datasheet Performance Curves


SR2B121BD

Compact and Modular Smart Relays

Electrical Durability of Relay Outputs

(in millions of operating cycles, conforming to IEC/EN 60947-5-1)

DC-12 (1)




X: Current (A)

Y: Millions of operating cycles

(1) DC-12: control of resistive loads and of solid state loads isolated by opto-coupler, $L/R \le 1$ ms.





X: Current (A)

Y: Millions of operating cycles

(1) DC-13: switching electromagnets, L/R ≤ 2 x (Ue x le) in ms, Ue: rated operational voltage, le: rated operational current (with a protection diode on the load,